

How to unlock SafeNet 5110cc



ADACOM

SECURITY BUILT ON TRUST

°°°°

2 Page

1. How to unlock SafeNet 5110cc Token Password

(The following procedure concerns USB Tokens that have been supplied by ADACOM and the user has not changed the Administrator password or PUK)

• Double click on the **"Safenet Authentication Client Tools"** icon at the right side of your computer screen



• Select "Advanced View" by pressing on the gear icon as shown in the picture below.

Kreontos 25, GR 10442 Athens, T: +30 210 5193740

http: <u>www.adacom.com</u> email: <u>customer-support@adacom.com</u>

ADACOM			SECURITY BUIL	T ON TRUST
	SafeNet Authentication Client Tools			5
	SafeNet Authen	tication Client	Token	
	02Mero CCID SC Reader 0		n Password Token n Cortent en Info	<u></u> •••
	< >>	Discorrect. SafeN	et Virtual Token ⊖ GEMALTO.COM	

• Press on the "Set Token Password" icon as shown in the picture below.

ntication Clier	nt 🛛 🕸 🚳 🕯 🤋 🚖
◎₽₽≋∕₽₽∎	6 2 0
Token name	Card #7D6CE0BB6FC79875
Taken category	Hardware
Readername	AKS ifdh 0
Senal number (PKCS#11)	7D6CE0886FC79875
Free space (minimum estimated)	26476
Hardware version	16.0
Firmware version	16.1
Card ID (GUID)	0x58000008FD28107658000008FD281076
Product name	SafeNet eToken 5110 CC
Model	Token 16.0.0.0 16.1.1
Card type	ID Prime MD
Applet Version	IDPrime Java Applet 4.0.2.K
Mask version	G260/Fit17
Color	N/A
Supported key size	2048 bits
Token Password	Present
Token Password ratries remaining	3
Maximum Token Password retries	3
	Atication Client

Give the Administrator Password

> http: <u>www.adacom.com</u> email: <u>customer-support@adacom.com</u>

3 Page

ADACOM	SECURITY BUILT ON TRUST
	Safehte Authentication Client Tools
	SafeNet Authentication Client
• Set your new Tok	een password, confirm it and click OK Set Password: Card #7A246689D5373D7E × SafeNet Authentication Client
	Token Password: Confirm Password: Token password must be changed on first logon The new password must comply with the quality settings defined on the token. A secure password has at least 8 characters, and contains upper-case letters, lower-case letters, numerals, and special characters (such as 1, \$, #, %). Current Language: EN Enter a new password.
Kreontos	25, GR 10442 Athens, T: +30 210 5193740
	http: www.adacom.com

ADACOM

SECURITY BUILT ON TRUST

0

^{′°}°°°

5 Page

- 2. How to unlock SafeNet 5110cc Token Pin
 - Double click on the "Safenet Authentication Client Tools" icon at the right side of your computer screen



Select "Advanced View" by pressing on the gear icon as shown in the picture below. •

Kreontos 25, GR 10442 Athens, T: +30 210 5193740

http: www.adacom.com email: <u>customer-support@adacom.com</u>

ADACOM			SEC	URITY BUILT ON TR	UST	եր Տե
	© SafeNet Authentication Client Tools	ntication Clie	geme ent		5	
	Card #706CE0886FC79875	/ **** © ©	Pename Token Change Token Password Unlick Token Delete Token Cortent Vew Token Info Disconnect SafeNet Wrtual Token			, ,
Press on the	"Set Digital Signatu	re PIN" icon a	⊕ @EMALTO.C	ure below		
	SafeNet Auther Safetlet Authentication Client Tools Safetlet Authentication Client Tools Safetlet Safe	Tication Cl Construction Cl Construction Token name Token name Token name Send number (PKCS#11) Free space (inimum estimated) Card ID (SUU) Product name Card ID (SUU) Product name	THAL ient ient ient	.ES Î		, ,
		Token Password retries remaining Maximum Token Password retries Token Password septration Administrator Password FIPS Prefile Common Citteria (CC) Profile Token unlock objects	5 5 No expiration Present N/A CC EALS- / PP QSCD Administrator thalkesgroup.	com		[]

6 Page

http: www.adacom.com email: <u>customer-support@adacom.com</u>

Set the digital signature **PUK** 6 zeros (000000) and click **OK**.

Kreontos 25, GR 10442 Athens, T: +30 210 5193740

	Security Built on Trust
	Digital Signature PUK Logon
	SafeNet Authentication Client genalto
	Enter the Digital Signature PUK:
	Token Name: Card #7A2466B9D5373D7E
	Digital Signature PUK:
	Current Language: EN
	OK Cancel
• Set	your new digital signature PIN, confirm it and click OK
	Set PIN: Card #7A2466B9D5373D7E
	SafeNet Authentication Client
	SafeNet Authentication Client
	Set PIN: Card #7A2466B9D5373D7E SafeNet Authentication Client New Digital Signature PIN: Confim PIN:
	Set PIN: Card #7A2466B9D5373D7E SafeNet Authentication Client New Digital Signature PIN: Confirm PIN: Token PIN must be changed on first logon
	Set PIN: Card #7A2466B9D5373D7E SafeNet Authentication Client New Digital Signature PIN: Confirm PIN: Token PIN must be changed on first logon The new PIN must comply with the quality settings defined on the token.
	Set PIN: Card #7A2466B9D5373D7E SafeNet Authentication Client New Digital Signature PIN: Confirm PIN: Token PIN must be changed on first logon The new PIN must comply with the quality settings defined on the token. A secure PIN has at least 8 characters, and contains upper-case letters, lower-case letters, numerals, and exercise characters (upp as 1.5 of 20)
	Set PIN: Card #7A246689D5373D7E SafeNet Authentication Client New Digital Signature PIN: Confirm PIN: Token PIN must be changed on first logon The new PIN must comply with the quality settings defined on the token. A secure PIN has at least 8 characters, and contains upper-case letters, lower-case letters, numerals, and special characters (such as 1, \$, #, %). Current Language: EN
	Set PIN: Card #7A246689D5373D7E SafeNet Authentication Client New Digital Signature PIN: Corfim PIN: Token PIN must be changed on first logon The new PIN must comply with the quality settings defined on the token. A secure PIN has at least 8 characters, and contains upper-case letters, lower-case letters, numerals, and special characters (such as 1, \$, #, %). Current Language: EN Enter a new PIN. OK Carel
	Set PIN: Card #7A246689D5373D7E SafeNet Authentication Client New Digital Signature PIN: Confirm PIN: Token PIN must be changed on first logon The new PIN must comply with the quality settings defined on the token. Asecure PIN has at least 8 characters, and contains upper-case letters, lower-case letters, numerals, and special characters (such as 1, \$, #, %). Current Language: EN Enter a new PIN. Kancel
	Set PIN: Card #7A246689D5373D7E SafeNet Authentication Client New Digital Signature PIN: Confirm PIN: Token PIN must be changed on first logon The new PIN must comply with the quality settings defined on the token. A secure PIN has at least 8 characters, and contains upper case letters, lower case letters, numerals, and special characters (such as 1, \$, #, %). Current Language: Enter a new PIN. OK
	Set PIN: Card #7A246689D5373D7E SafeNet Authentication Client New Digital Signature PIN: Confirm PIN: The new PIN must be changed on first logon The new PIN must comply with the quality settings defined on the token. A secure PIN has at least 8 characters, and contains upper case letters, lower case letters, numerals, and special characters (such as 1, \$, #, %). Current Language: EN Enter a new PIN. Kreontos 25, GR 10442 Athens, T: +30 210 5193740
	Set PIN: Card #7A246689D5373D7E SafeNet Authentication Client New Digital Signature PIN: Confirm PIN: Token PIN must be changed on first logon The new PIN must comply with the quality settings defined on the token. A secure PIN has at least 8 characters, and contains upper case letters, lower-case letters, numerals, and special characters (such as 1, \$, #, %). Current Language: EN Enter a new PIN. Kreontos 25, GR 10442 Athens, T: +30 210 5193740
	Set PIN: Card #7A246689D5373D7E SafeNet Authentication Client New Digital Signature PIN: Corfim PIN: The new PIN must be changed on first logon The new PIN must comply with the quality settings defined on the token. A secure PIN has at least 8 characters, and contains upper-case letters, numerals, and special characters (such as 1, \$, #, %). Current Language: EN Enter a new PIN. Kreontos 25, GR 10442 Athens, T: +30 210 5193740 http::::www.adacom.com mail:::ustomer-support@adacom.com
	Set PIN: Card #7A246689D5373D7E SafeNet Authentication Client New Digital Signature PIN: Confirm PIN Token PIN must be changed on first logon The new PIN must comply with the quality settings defined on the token. A secure PIN has at least 8 characters, and contains upper-case letters, lower-case letters, numerals, and going and
	Set PIN: Card #7A2466890D5373D7E SafeNet Authentication Client New Digital Signature PIN Confirm PIN Token PIN must be changed on first logon Token PIN must comply with the quality settings defined on the token. Asecure PIN has at least 8 characters, and contains upper case letters, lower case letters, numerals, and special characters (such as I, S, #, %). Current Language: EN Teter a new PIN. Kreontos 25, GR 10442 Athens, T: +30 210 5193740 Kreontis 25, GR 10442 Athens, T: +30 210 5193740 Mtp: www.adacom.com
	Set PIN: Card #7A246689D5373D7E SafeNet Authentication Client New Digital Signature PIN: Corfirm PIN Token PIN must comply with the quality settings defined on the token. A secure PIN has at least 8 characters, and contains upper case letters, numerals, and special characters (such as 1, \$, #, %). Current Language: EN Enter a new PIN Kreontos 25, GR 10442 Athens, T: +30 210 5193740 Kreontos 25, GR 10442 Athens, T: +30 210 5193740 Attp: www.adacom.com